



ELNIX, since 1995 is the forerunner in power electronics industry, which is going through a 360 change. High performance, Advanced DSP based Pure Sine Wave Digital Home UPS is brought to by ELNIX. It has the exclusively capability to provide longer backup with an adequate variable charging cirrent (4 mode charging with SMPS). It has advance Digital Signal Processor to control the input and out put parameters automatically.

TECHNOLOGY

Highly efficient MOSFET based DSP Technology.

APPLICATIONS

Supports both computer & Light (mixed load design).

FUNCTIONS

The battery through DC-startup function can directly start Digital UPS in absence of power.

SMART CHARGER

Battery level Auto sense charging ensure quick and efficient charging of battery even at very low input supply volt conditions. Different step of charging with boost, trickle and float and drop charging (4 mode) assures good health of the battery more than other inverters.

LOAD CHART											
Rating		600VA			800VA			1000VA			
2.252	Chart A	Chart B	Chart C	Chart A	Chart B	Chart C	Chart A	Chart B	Chart C		
Fan	2	3	2	3	4	3	4	5	6		
Tube Light	3	4	3	4	6	4	6	6	6		
Television	1			1			2	1	0		
Computer			1			1	1	1	2		

TECHNICAL SPECIFICATIONS						
	Model	600 VA / 800 VA / 11000 VA				
Input	Phase	Single Phase				
	Frequency	50 Hz <u>+</u> 5%				
	Voltage	90V-300V AC + 5% Normal Mode 180V - 260V AC + 5% UPS Mode				
Output	Frequency	50 Hz <u>+</u> 1%				
	Wave Form	Pure Sine Wave				
	Voltage	12 VDC				
	Charging Current	SMPS Varriable Switch				
Panel Display	LDC	Temp, Batt. Volt, Output Volt, Charging mode, Current Battery Condition. Input Volt frequently, Working mode				
Alarms	Веер	Change over time, battery low, overload				
	Temperature	0°C to 46°C				
	Humidity	Upto 90% (Non Condensing)				
General	Dimension	L x W x H (mm) 250 x 275 x 125				
	Net. Weight	8.5 - 12 Kg				
Warranty		Detailed on Card				

The unit is designed with Auto Reset feature. The unit gives alarm beep, the unit resets automatically and functions normally, In case of continuous overload condition, UPS goes to Auto Shut off mode.

Fully silent operations in all mode(invertor, chaging, and out put)

Reverse phase protection.

Selector switch for UPS and Normal mode.

Automatic temperature control features (ATC tech) to prevent over heat and distortions.







WE PROVIDED ALL MAJOR BRANDS OF BATTERIES
AND AMC FOR ALL BRANDS
EXCHANGE AND UP GRADATION
ALSO PROVIDED WITH BEST OFFERS

l leal	r



ELNIX POWER SYSTEMS

'THADATHIL', Poonithura P.O., Petta, Emakulam - 682 038 Tel: 0484 - 2301736, 9447878382, Fax: 0484 - 2301736

E-mail: elnixpowersystems@gmail.com